

# Process Overview of Using Scan2Stage

This article describes the process of using Scan2Stage.

You can create a profile as JSON format, and provision your devices with the profile.



## 1. Creating a Profile

- 1) Launch Scan2Stage and determine the configurations as you want.
- 2) Save as JSON file and Upload the JSON file to web-based server (ex.Dropbox)

## 2. Provisioning Devices with JSON

Determine provisioning method among QR Code, Automatic Provisioning, PMDM.

---

## APPLIES TO

Scan2Stage v20.0.0 and above

---

## 1. Make Configurations

Configuration	Description
Task	<ul style="list-style-type: none"><li>• Set the schedule for when the JSON file will be applied to your device.</li><li>• Add and order the tasks which are applied to your device through EmInstaller</li></ul>
Kiosk	<ul style="list-style-type: none"><li>• Set the EmKiosk configurations</li></ul>
Device	<ul style="list-style-type: none"><li>• Set the device configuration &amp; setting values</li></ul>
Scanner	<ul style="list-style-type: none"><li>• Set the scanner setting values</li></ul>
RingControl	<ul style="list-style-type: none"><li>• Set the RingControl configuration for ring scanner (PM5)</li></ul>
WedgeProfile	<ul style="list-style-type: none"><li>• Set the WedgeProfiler configuration</li></ul>
GmsPackage	<ul style="list-style-type: none"><li>• Enable/Disable all or some of GMS Package application</li></ul>
OsUpdate	<ul style="list-style-type: none"><li>• Set OS update action values</li></ul>

## BatteryMonitor

- Set EmBatteryMonitor notification settings

## 2. Save as JSON File and Upload

- Tap File > Save/Save As to save the configurations (JSON file)
- Upload the JSON file and PMDMAgent (EmInstaller) to web-based server (ex. Dropbox)


## 3. Generate QRCode

- Click **Generating QR Code** on the upper-right side of the Scan2Stage console.



- Enter the information for provisioning process.


### CA File Information (Optional)



Certificate information to be used for connecting Wi-Fi.

**Optional:** If the network security type not requires CA certificate information, no need to input.

### Network Settings (Optional)



Wi-Fi information (SSID, Password, Security Type, etc.) to be used for provisioning process.

**Optional:** If your device already connected proper Wi-Fi, no need to input.

### EmInstaller Settings (Partially Required)



Configuration File	<b>(Optional)</b> If you uploaded Zip file which contains apk or app data file on step 1, input its URL here.
JSON File Name	<b>(Required)</b> Input URL of JSON file you uploaded on step 1.
EmInstaller APK	<b>(Optional)</b> If you uploaded PMDMAgent (EmInstaller) apk file on step 1, input its URL here. PMDMAgent (EmInstaller) will be installed or updated with this information.
Screen timeout	Check this option to turn on the screen all the time during provisioning process.

### Input Direct Download Link

When inputting URLs in EmInstaller Setup section, you must input the direct download link. Refer to [Direct Download Link](#).

## QR Code Settings (Optional)





Turn on the switch (Enable) if you want to provision devices with the same profile after factory reset.

Refer to [Using Automatic Provisioning](#) for more detail.

**Optional:** If you want to provision devices only once, skip this setting.

## 4. Scan the QRCode

- Scan the QR code
- (On the setup wizard) Press the scan button after the  icon is displayed on the status bar  
(On the home screen) Launch EmKit > Scan2Set and scan



If the system is locked with [FRP \(Factory Reset Protection\)](#), the provisioning cannot be performed.